# CHIP COIL (CHIP INDUCTOR) for Automotive powertrain/safety equipment LQH43NH \( \subseteq \subseteq 03L \) Murata Standard Reference Specification [AEC-Q200]

### 1. Scope

This reference specification applies to LQH43NH 03 series based on AEC-Q200.

#### 1.1 Specific applications:

- Automotive powertrain/safety equipment: Products that can be used for automotive equipment related to running, turning, stopping, safety devices, etc., or equipment whose structure, equipment, and performance are legally required to meet technical standards for safety assurance or environmental protection.
- · Automotive infotainment/comfort equipment: Products that can be used for automotive equipment such as car navigation systems and car audio systems that do not directly relate to human life and whose structure, equipment, and performance are not specifically required by law to meet technical standards for safety assurance or environmental protection.
- · Medical equipment (GHTF Class C) \*Except for implant/surgery/auto injector: Products that can be used for medical equipment of Class C of the international classification class GHTF and whose malfunction is considered to pose a relatively high risk to the human body.
- · Medical equipment (GHTF Class A and B): Products that can be used for medical equipment regulated by Class A and Class B of the international classification class GHTF and whose functions do not directly relate to the protection of human life and property.

#### 1.2 Unsuitable application:

Applications listed in "Limitation of applications" in this reference specification.

2.Part	N	lum	be	rin	g
--------	---	-----	----	-----	---

(ex)	<u>LQ</u>	H	43	N	H	1R0	М	0	3	L
	Product ID	Structure	Dimension	Applications	Category	Inductance	Tolerance	Features	Electrode	Packaging
			(L×W)	and						L:Taping
				Characteristics						

# 3.Rating

Operating Temperature Range.
 Storage Temperature Range.
 -40 °C to +125 °C
 -40 °C to +125 °C

Customer's	MURATA	Ind	luctance	Q	DC Re	sistance	Self Resonant	*1:Rated	ESD		
Part Number	Part Number	(μΗ)	Tolerance (%)	(min.)	(Ω)	Tolerance (%)	Frequency (MHz min)	Current (mA)	5A: 8kV		
	LQH43NH1R0M03L	1.0	M: ±20		0.033		120	1300			
	LQH43NH1R2K03L	1.2	K: ±10		0.043		100	1100			
	LQH43NH1R5J03L	1.5			0.049		85	1000			
	LQH43NH1R8J03L	1.8			0.043		75	1050			
	LQH43NH2R2J03L	2.2		20	0.049		62	1000			
	LQH43NH2R7J03L	2.7			0.053		53	950			
	LQH43NH3R3J03L	3.3			0.077		47	800			
	LQH43NH3R9J03L	3.9		7			0.12		41	650	5.4
	LQH43NH4R7J03L	4.7				0.090	±20	38	750	5A	
	LQH43NH5R6J03L	5.6	J: ±5	25	0.11		33	650			
	LQH43NH6R8J03L	6.8			0.18		31	530			
	LQH43NH8R2J03L	8.2		30	0.18		27	530			
	LQH43NH100J03L	10			0.20		23	480			
	LQH43NH120J03L	12		0.5	0.25		21	420			
	LQH43NH150J03L	15		35	0.30		19	390			
	LQH43NH180J03L	18			0.35		17	365			

Customer's	MURATA	Ind	uctance	Q	DC R	esistance	Self Resonant	*1:Rated	ESD
Part Number	Part Number	(μH)	Tolerance (%)	(min.)	(Ω)	Tolerance (%)	Frequency (MHz min)	Current (mA)	5A: 8kV
	LQH43NH220J03L	22			0.47		15	300	
	LQH43NH270J03L	27			0.60		14	280	
	LQH43NH330J03L	33			0.70		12	250	
	LQH43NH390J03L	39		0.5	0.80		11	230	
	LQH43NH470J03L	47		35	0.87		10	210	
	LQH43NH560J03L	56			1.34		9.3	180	
	LQH43NH680J03L	68			1.52		8.4	170	
	LQH43NH820J03L	82			1.70		7.5	165	
	LQH43NH101J03L	100			2.00		6.8	150	
	LQH43NH121J03L	120			2.60		6.2	130	
	LQH43NH151J03L	150			3.00		5.5	120	
	LQH43NH181J03L	180			3.40		5.0	110	
	LQH43NH221J03L	220	J: ±5		3.80	±20	4.5	100	5A
	LQH43NH271J03L	270			5.50		4.0	90	
	LQH43NH331J03L	330			6.20		3.6	85	
	LQH43NH391J03L	390			6.90		3.3	80	
	LQH43NH471J03L	470		40	7.80		3.0	75	
	LQH43NH561J03L	560			11.3		2.7	60	
	LQH43NH681J03L	680			12.9		2.5	55	
	LQH43NH821J03L	820			14.5		2.2	50	
	LQH43NH102J03L	1000			15.5		2.0	45	
	LQH43NH122J03L	1200			20.3		1.8	40	
	LQH43NH152J03L	1500			23.7		1.6	35	
	LQH43NH182J03L	1800			26.7		1.5	35	
	LQH43NH222J03L	2200			30.6		1.3	30	

<sup>\*1:</sup>When applied Rated current to the Products, self temperature rise shall be limited to 20°C max and Inductance will be within ±10% of nominal value.

# 4. Testing Conditions

《Unless otherwise specified》 《In case of doubt》


Temperature : Ordinary Temperature /  $15^{\circ}$ C to  $35^{\circ}$ C Temperature :  $20 \pm 2^{\circ}$ C

Humidity: Ordinary Humidity / 25%(RH) to 85%(RH) Humidity: 60%(RH) to 70%(RH)

Atmospheric Pressure: 86kPa to 106 kPa



# 5.Appearance and Dimensions (No marking)



# 6. Electrical Performance

No.	Item	Specification	Test Method
6.1	Inductance	Inductance shall meet item 3.	Measuring Equipment:  KEYSIGHT 4192A or equivalent Measuring Frequency:  1MHz / 1.0 to 390µH  1kHz / 470 to 2200µH
6.2	Q	Q shall meet item 3.	Measuring Equipment: KEYSIGHT 4192A or equivalent Measuring Frequency: 1MHz / 1.0 to 82µH 796kHz / 100 to 820µH 252kHz / 1000 to 2200µH
6.3	DC Resistance	DC Resistance shall meet item 3.	Measuring Equipment:Digital multi meter
6.4	Self Resonant Frequency(S.R.F)	S.R.F shall meet item 3.	Measuring Equipment: KEYSIGHT E4991A or equivalent


# 7. AEC-Q200 Requirement

# 7.1 Performance (based on Table 5 for Magnetics(Inductors / Transformer) AEC-Q200 Rev.D issued June. 1 2010

	AEC-Q200			Murata Specification / Deviation		
No	Stress	Test Method		Murata Specification	on / Deviation	
3	High Temperature	1000hours at 125 deg C Set for 24hours at room	Meet Table A after testing.			
	Exposure	temperature, then measured.		Appearance Inductance change	No damage Within ±10%	
				madetance change	VVICINI 21070	
4	Temperature Cycling	1000cycles -40 deg C to + 125 deg C Set for 24hours at room temperature,then measured.	Meet Table A after testing.			
7	Biased Humidity	1000hours at 85 deg C, 85%RH unpowered.	Meet Table A after testing.			
8	Operational Life	Apply 125 deg C 1000 hours Set for 24hours at room temperature, then measured	Meet Table A after testing.			
9	External Visual	Visual inspection	No abnorm	alities		

No		AEC-Q200	N . O . T . T . D . T		
	Stress	Test Method	Murata Specification / Deviation		
10	Physical Dimension	Meet ITEM 5 (Appearance and Dimensions)	No defects		
12	Resistance to Solvents	Per MIL-STD-202 Method 215	Not Applicable		
13	Mechanical Shock	Per MIL-STD-202 Method 213 100g's/6ms/Half sine	Meet Table A after testing.		
14	Vibration	5g's for 20 minutes, 12cycles eah of 3 orientations Test from 10-2000Hz. 12cycles each of 3 orientations	Meet Table A after testing.		
15	Resistance to Soldering Heat	No-heating Solder temperature 260C+/-5 deg C Immersion time 10s	Meet Table A after testing.		
17	ESD	Per AEC-Q200-002	Meet Item 3 (Rating) No defects		
18	Solderbility	Per J-STD-002	Method B : Not Applicable 95% of the terminations is to be soldered. (Except exposed wire)		
19	Electrical Characterization	Measured : Inductance	No defects		
20	Flammability	Per UL-94	Not Applicable		
21	Board Flex	Epoxy-PCB(1.6mm) Deflection 2mm(min) 60s minimum holding time	Murata deviation request: 5s Meet Table B after testing. Table B		
			Appearance No damage		
			DC resistance change Within ±10%		
22	Terminal Strength	Per AEC-Q200-006 A force of 17.7N for 60s	No defects		

# 8. Specification of Packaging 8.1 Appearance and Dimensions of plastic tape



The packing directions of the chip coil in taping are unified with the in/out positions of the lead wire.

Dimension of the Cavity is measured at the bottom side.

# 8.2 Specification of Taping

(1) Packing quantity (standard quantity)

500 pcs / reel

(2) Packing Method

Products shall be packed in the each embossed cavity of plastic tape and sealed by cover tape.

(3) Sprocket hole

The sprocket holes are to the right as the tape is pulled toward the user.

(4) Spliced point

Plastic tape and Cover tape has no spliced point.

(5) Missing components number


Missing components number within 0.025 % of the number per reel or 1 pc., whichever is greater, and are not continuous. The specified quantity per reel is kept.

### 8.3 Pull Strength

Plastic tape	10N min.
Cover tape	5N min.


# 8.4 Peeling off force of cover tape

Speed of Peeling off	300mm / min
Peeling off force	0.2N to 0.7N (minimum value is typical)



### 8.5 Dimensions of Leader-tape, Trailer and Reel

There shall be leader-tape (cover tape) and trailer-tape (empty tape) as follows.



### 8.6 Marking for reel

Customer part number, MURATA part number, Inspection number(\*1), RoHS marking(\*2), Quantity etc · · ·

\*1) < Expression of Inspection No.>

 $\frac{\square \square}{(1)} \frac{OOOO}{(2)} \frac{\times \times \times}{(3)}$ 

(1) Factory Code

(2) Date First digit : Year / Last digit of year

Second digit : Month / Jan. to Sep.  $\rightarrow$  1 to 9, Oct. to Dec.  $\rightarrow$  O, N, D

Third, Fourth digit : Day

(3) Serial No.

\*2) « Expression of RoHS marking » ROHS  $-\underline{Y}$  ( $\triangle$ )

(1) RoHS regulation conformity


(2) MURATA classification number

#### 8.7 Marking for Outside package (corrugated paper box)

Customer name, Purchasing order number, Customer part number, MURATA part number, RoHS marking (\*2) ,Quantity, etc ···



#### 8.8. Specification of Outer Case



Outer Ca	se Dimensi	Standard Reel Quantity	
W	D	Н	in Outer Case (Reel)
186	186	93	5

<sup>\*</sup>Above Outer Case size is typical. It depends on a quantity of an order

#### 9. A Caution

# 9.1 Limitation of applications

The products listed in the reference specification (hereinafter the product(s) is called as the "Product(s)") are designed and manufactured for applications specified in the reference specification (hereinafter called as the "Specific Application").

We shall not warrant anything in connection with the Products including fitness, performance, adequateness, safety, or quality, in the case of applications listed in from (1) to (11) written at the end of this precautions, which may generally require high performance, function, quality, management of production or safety. Therefore, the Product shall be applied in compliance with the specific application.

WE DISCLAIM ANY LOSS AND DAMAGES ARISING FROM OR IN CONNECTION WITH THE PRODUCTS INCLUDING BUT NOT LIMITED TO THE CASE SUCH LOSS AND DAMAGES CAUSED BY THE UNEXPECTED ACCIDENT, IN EVENT THAT (i) THE PRODUCT IS APPLIED FOR THE PURPOSE WHICH IS NOT SPECIFIED AS THE SPECIFIC APPLICATION FOR THE PRODUCT, AND/OR (ii) THE PRODUCT IS APPLIED FOR ANY FOLLOWING APPLICATION PURPOSES FROM (1) TO (11) (EXCEPT THAT SUCH APPLICATION PURPOSE IS UNAMBIGUOUSLY SPECIFIED AS SPECIFIC APPLICATION FOR THE PRODUCT IN OUR CATALOG SPECIFICATION FORMS, DATASHEETS, OR OTHER DOCUMENTS OFFICIALLY ISSUED BY US\*).

- (1) Aircraft equipment
- (2) Aerospace equipment
- (3) Undersea equipment
- (4) Power plant control equipment
- (5) Medical equipment
- (6) Transportation equipment
- (7) Traffic control equipment
- (8) Disaster prevention/security equipment
- (9) Industrial data-processing equipment
- (10) Combustion/explosion control equipment

(11) Equipment with complexity and/or required reliability equivalent to the applications listed in the above. For exploring information of the Products which will be compatible with the particular purpose other than those specified in the reference specification, please contact our sales offices, distribution agents, or trading companies with which you make a deal, or via our web contact form.

Contact form: https://www.murata.com/contactform

\* We may design and manufacture particular Products for applications listed in (1) to (11). Provided that, in such case we shall unambiguously specify such Specific Application in the reference specification without any exception. Therefore, any other documents and/or performances, whether exist or non-exist, shall not be deemed as the evidence to imply that we accept the applications listed in (1) to (11).

#### 9.2 Caution(Rating)

Do not exceed maximum rated current of the product. Thermal stress may be transmitted to the product and short/open circuit of the product or falling off the product may be occurred.

## 9.3 Fail-safe

Be sure to provide an appropriate fail-safe function on your product to prevent a second damage that may be caused by the abnormal function or the failure of our product.

#### 9.4 Corrosive gas

Please refrain from use since contact with environments with corrosive gases (sulfur gas [hydrogen sulfide, sulfur dioxide, etc.], chlorine, ammonia, etc.) or oils (cutting oil, silicone oil, etc.) that have come into contact with the previously stated corrosive gas environment will result in deterioration of product quality or an open from deterioration due to corrosion of product electrode, etc. We will not bear any responsibility for use under these environments.



# 10. Notice

This product is designed for solder mounting.


Please consult us in advance for applying other mounting method such as conductive adhesive.

### 10.1 Land pattern designing

Recommended land patterns for reflow soldering are as follows:

It has been designed for Electric characteristics and solderability.

Please follow the recommended pattern. Otherwise, their performance which includes electrical performance or solderability may be affected, or result to "position shift" in soldering process.



# 10.2 Flux, Solder

Flux	<ul> <li>Use rosin-based flux.</li> <li>Don't use highly acidic flux with halide content exceeding 0.2(wt)% (chlorine conversion value).</li> <li>Don't use water-soluble flux.</li> </ul>
Solder	<ul><li>Use Sn-3.0Ag-0.5Cu solder</li><li>Standard thickness of solder paste : 200μm to 300μm</li></ul>

Other flux (except above) Please contact us for details, then use.


#### 10.3 Reflow soldering conditions

• Pre-heating should be in such a way that the temperature difference between solder and product surface is limited to 150°C max. Cooling into solvent after soldering also should be in such a way that the temperature difference is limited to 100°C max.

Insufficient pre-heating may cause cracks on the product, resulting in the deterioration of products quality.

Standard soldering profile and the limit soldering profile is as follows.
 The excessive limit soldering conditions may cause leaching of the electrode and / or resulting in the deterioration of product quality.

#### · Reflow soldering profile



	Standard Profile	Limit Profile		
Pre-heating	150~180°C 、90s±30s			
Heating	above 220°C、30s∼60s	above 230°C、60s max.		
Peak temperature	245±3°C	260°C,10s		
Cycle of reflow	2 times	2time		

# Spec No. JELF243A-9150C-01

# Reference Only

### 10.4 Reworking with soldering iron.

The following conditions must be strictly followed when using a soldering iron.

Pre-heating	150°C,1 min
Tip temperature	350°C max.
Soldering iron output	80W max.
Tip diameter	$\phi$ 3mm max.
Soldering time	3(+1,-0)s
Times	2 times

Note: Do not directly touch the products with the tip of the soldering iron in order to prevent the crack on the products due to the thermal shock.

#### 10.5 Solder Volume

- Solder shall be used not to be exceeded the upper limits as shown below.
- Accordingly increasing the solder volume, the mechanical stress to Chip is also increased.
   Exceeding solder volume may cause the failure of mechanical or electrical performance.




1/3T≦t≦T

T: Lower flange thickness

#### 10.6 Product's location

The following shall be considered when designing and laying out P.C.B.'s.

(1) P.C.B. shall be designed so that products are not subject to the mechanical stress due to warping the board.




The electorode part of the products should be located like the picture to the mechanical stress.

(2) Components location on P.C.B. separation.

It is effective to implement the following measures, to reduce stress in separating the board. It is best to implement all of the following three measures; however, implement as many measures as possible to reduce stress.


Contents of Measures	Stress Level
(1) Turn the mounting direction of the component parallel to the board separation surface.	A > D*1
(2) Add slits in the board separation part.	A > B
(3) Keep the mounting position of the component away from the board separation surface.	A > C



\*1 A > D is valid when stress is added vertically to the perforation as with Hand Separation.
If a Cutting Disc is used, stress will be diagonal to the PCB, therefore A > D is invalid.

(3) Mounting Components Near Screw Holes
When a component is mounted pear as

When a component is mounted near a screw hole, it may be affected by the board deflection that occurs during the tightening of the screw. Mount the component in a position as far away from the screw holes as possible.





#### 10.7 Cleaning Conditions

Products shall be cleaned on the following conditions.

- (1) Cleaning temperature shall be limited to 60°C max.(40°C max for alcohol type cleaner.)
- (2) Ultrasonic cleaning shall comply with the following conditions with avoiding the resonance phenomenon at the mounted products and P.C.B.

Power: 20 W / I max. Frequency: 28kHz to 40kHz Time: 5 min max.

- (3) Cleaner
  - 1. Alternative cleaner
    - · Isopropyl alcohol (IPA)
  - 2. Aqueous agent
    - PINE ALPHA ST-100S
- (4) There shall be no residual flux and residual cleaner after cleaning.

In the case of using aqueous agent, products shall be dried completely after rinse with de-ionized water in order to remove the cleaner.

(5) Other cleaning

Please contact us.

# 10.8 Resin coating (moistureproof coating)

Do not make any resin coating.

The inductance value may change due to high cure-stress of resin to be used for coating/molding products. An open circuit issue may occur by mechanical stress caused by the resin, amount/cured shape of resin, or operating condition etc. Some resin contains some impurities or chloride possible to generate chlorine by hydrolysis under some operating condition may cause corrosion of wire of coil, leading to open circuit.

#### 10.9 Caution for use

- Sharp material such as a pair of tweezers or other material such as bristles of cleaning brush, shall not be touched to the winding portion to prevent the breaking of wire.
- · Mechanical shock should not be applied to the products mounted on the board to prevent the breaking of the core

### 10.10 Handling of a substrate

After mounting products on a substrate, do not apply any stress to the product caused by bending or twisting to the substrate when cropping the substrate, inserting and removing a connector from the substrate or tightening screw to the substrate.

Excessive mechanical stress may cause cracking in the product.

Bending

Twisting



# 10.11 Storage and Handing Requirements

(1) Storage period

Use the products within 12 months after delivered.

Solderability should be checked if this period is exceeded.

- (2) Storage conditions
  - Products should be stored in the warehouse on the following conditions.

Temperature : -10 °C to 40 °C

Humidity: 15 % to 85 % relative humidity. No rapid change on temperature and humidity. The electrode of the products is coated with solder. Don't keep products in corrosive gases such as sulfur, chlorine gas or acid, or it may cause oxidization of electrode, resulting in poor solderability.

- Products should not be stored on bulk packaging condition to prevent the chipping of the core and the breaking
  of winding wire caused by the collision between the products.
- ${f \cdot}$  Products should be stored on the palette for the prevention of the influence from humidity, dust and so on.
- · Products should be stored in the warehouse without heat shock, vibration, direct sunlight and so on.
- (3) Handling Condition

Care should be taken when transporting or handling product to avoid excessive vibration or mechanical shock.

### 11. **A** Note

- (1) Please make sure that your product has been evaluated in view of your specifications with our product being mounted to your product.
- (2) You are requested not to use our product deviating from the reference specifications.
- (3) The contents of this reference specification are subject to change without advance notice. Please approve our product specifications or transact the approval sheet for product specifications before ordering.